



SCHMATIC VIEWED FROM BASE END
 FUSE RECOMMENDED BUT NOT SUPPLIED

SPECIFICATIONS											
WIRING	INPUT		OUTPUT				SHAFT ROTATION FOR VOLTAGE INCREASE	TERMINAL CONNECTIONS			
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		FOR INCREASING VOLTAGE AS VIEWED FROM BASE END			
				MAX. AMPS	MAX. KVA	MAX. AMPS		MAX. KVA	INPUT	JUMPER	OUTPUT
SINGLE PHASE	120	50/60	0-120	15	1.80	20	2.40	CW	2-4	---	4-3
			0-140	15	2.10	---	---	CCW	2-4	---	2-3
								CW	1-4	---	4-3
			CCW	5-2	---	2-3					

UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ±				ALL DIMENSIONS APPLY AFTER PLATING		TITLE: SPECIFICATION CONTROL DRAWING VARIABLE TRANSFORMER TYPE: 1510C		STACO ENERGY PRODUCTS CO. DAYTON, OHIO U.S.A.	
FRACTIONS 1/64	DECIMALS .0005	HOLES .002	ANGLES 1°	DRAFT 1-1/8°	MATERIAL:		FINISH:		
CAT #10		DRAWN BY: R. TOLLIVER		DATE: 5-12-91	FIRST USED ON:		CUSTOMER APPROVAL:		
LO NOT SCALE DWG.		CHECKER: S.A. SMITH		DATE: 11-14-91	WEIGHT APPROX: 15.75 LBS.		DWG. NO. 031-3650		
CODE IDENT NO. 83008		ENGINEER: JMR		DATE: 3/17/91	SCALE: NONE		DWG. SIZE: C		